



GT-dC2

dController®

dController® programmer for dLNB® and dMultiswitch®.



VIEW ONLINE

dLNB®
dMULTISWITCH®

“PROGRAM” Button for programming “on the roof”

Commands for EN50607

**LED indicators for: ON/OFF, Short Circuit, 0/22 KHz Presence,
13/18V output voltage, Vout low,
Transmission error, Busy, Done**

USB communications with PC

DiSEqC 2.0 communication

DC Supply Voltage: +12V from PSU or +13 to 18V from STB

Output Voltage Range: 12.5 to 20 DC

LOOP/Through for RF signal

Up to 5 dB insertion loss of RF loop-through

75 Ohms impedance for LNB output and Receiver input

Compact housing

SOFTWARE SUPPORT:



PACKAGING INFORMATION: CONTACT US FOR MORE DETAILS.

EAN CODE

5453001615622